




INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(51) International Patent Classification ⁶ : H04B 1/59	A2	(11) International Publication Number: WO 99/62196 (43) International Publication Date: 2 December 1999 (02.12.99)
(21) International Application Number: PCT/IB99/00880 (22) International Filing Date: 14 May 1999 (14.05.99) (30) Priority Data: 98890149.2 22 May 1998 (22.05.98) EP (71) Applicant: KONINKLIJKE PHILIPS ELECTRONICS N.V. [NL/NL]; Groenewoudseweg 1, NL-5621 BA Eindhoven (NL). (71) Applicant (for SE only): PHILIPS AB [SE/SE]; Kottbygatan 7, Kista, S-164 85 Stockholm (SE). (72) Inventor: AMTMANN, Franz; Prof. Holstlaan 6, NL-5656 AA Eindhoven (NL). (74) Agent: WEBER, Helmut; Prof. Holstlaan 6, NL-5656 AA Eindhoven (NL).		(81) Designated States: JP, European patent (AT, BE, CH, CY, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE). Published <i>Without international search report and to be republished upon receipt of that report.</i>

(54) Title: WRITE/READ DEVICE FOR COMMUNICATION WITH TRANSPONDERS, HAVING FIRST CODING MEANS AND SECOND CODING MEANS

**(57) Abstract**

A write/read device (1) for the contactless communication with at least one transponder has first coding means (4) for coding a data block (DB) in accordance with a first coding method, which first coding means (4) can generate at the most a given number of N coding signals (KI) per data block (DB) in accordance with this first coding method, and has second coding means (9) for coding a data block (DB) in accordance with a second coding method, which second coding means (9) can generate at the most a given number of M coding signals (KI) per data block (DB) in accordance with this second coding method, and has selection means (10) for the selection between the coding signals (KI) supplied by the first coding means (4) and the coding signals (KI) supplied by the second coding means (9).

FOR THE PURPOSES OF INFORMATION ONLY

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AL	Albania	ES	Spain	LS	Lesotho	SI	Slovenia
AM	Armenia	FI	Finland	LT	Lithuania	SK	Slovakia
AT	Austria	FR	France	LU	Luxembourg	SN	Senegal
AU	Australia	GA	Gabon	LV	Latvia	SZ	Swaziland
AZ	Azerbaijan	GB	United Kingdom	MC	Monaco	TD	Chad
BA	Bosnia and Herzegovina	GE	Georgia	MD	Republic of Moldova	TC	Togo
BB	Barbados	GH	Ghana	MG	Madagascar	TJ	Tajikistan
BE	Belgium	GN	Guinea	MK	The former Yugoslav Republic of Macedonia	TM	Turkmenistan
BF	Burkina Faso	GR	Greece	ML	Mali	TR	Turkey
BG	Bulgaria	HU	Hungary	MN	Mongolia	TT	Trinidad and Tobago
BJ	Benin	IE	Ireland	MR	Mauritania	UA	Ukraine
BR	Brazil	IL	Israel	MW	Malawi	UG	Uganda
BY	Belarus	IS	Iceland	MX	Mexico	US	United States of America
CA	Canada	IT	Italy	NE	Niger	UZ	Uzbekistan
CF	Central African Republic	JP	Japan	NL	Netherlands	VN	Viet Nam
CG	Congo	KE	Kenya	NO	Norway	YU	Yugoslavia
CH	Switzerland	KG	Kyrgyzstan	NZ	New Zealand	ZW	Zimbabwe
CI	Côte d'Ivoire	KP	Democratic People's Republic of Korea	PL	Poland		
CM	Cameroon	KR	Republic of Korea	PT	Portugal		
CN	China	KZ	Kazakhstan	RO	Romania		
CU	Cuba	LC	Saint Lucia	RU	Russian Federation		
CZ	Czech Republic	LI	Liechtenstein	SD	Sudan		
DE	Germany	LK	Sri Lanka	SE	Sweden		
DK	Denmark	LR	Liberia	SG	Singapore		
EE	Estonia						

Write/read device for communication with transponders, having first coding means and second coding means.

The invention relates to a write/read device designed for the contactless communication with at least one transponder and comprising data supply means for supplying at least one data block and including first coding means, by which first coding means a data block supplied by the data supply means and applied to said first coding means can be coded
5 in accordance with a first coding method and by which, as a result of the coding in accordance with this first coding method, at the most a given number N of coding signals representing a data block can be generated and supplied, and including carrier signal generating means for generating a carrier signal and including modulation means, to which modulation means the carrier signal and the coding signals can be applied and by which modulation means the carrier
10 signal can be modulated in accordance with the coding signals so as to generate and supply a modulated carrier signal corresponding to the number of coding signals and having the same number of modulation steps, and including transmission means, to which transmission means the modulated carrier signal can be applied in order to be transmitted to at least one transponder.

15 Such write/read device is commercially available in a variety of versions and is consequently known. The known write/read device includes coding means adapted to perform a bit-oriented coding method, wherein for coding a data block a given number N of bits can be coded, i.e. each bit can exhibit either the logic zero state or the logic one state, so that as a result of coding in accordance with this bit-oriented coding method at the most a given number
20 N of coding signals, i.e. coding pulses, which represent a data block can be generated. Such a bit-oriented coding method has the advantage that a component high transmission rate is attainable. However, such a coding method entails the problem that corresponding to each coding signal a modulation step occurs in the carrier signal, which is amplitude-modulated in the known write/read device, as a result of which during the transmission from the write/read
25 device to a transponder not only the amplitude-modulated carrier signal has a comparatively high amplitude but that, in addition, the amplitudes in the so-called sidebands may exhibit comparatively large values if many modulation steps occur, which in many countries gives rise to problems as regards statutory regulations relating to spurious emission and the limitation of spurious emission.

It is an object of the invention to preclude the afore-mentioned problems in a write/read device and to provide an improved write/read device during whose use no problems arise as regards statutory regulations relating to spurious emission and the limitation of spurious emission. According to the invention this object is achieved in a write/read device of the type defined in the opening paragraph in that there have been provided second coding means, by which second coding means a data block supplied by the data supply means and applied to said second coding means can be coded in accordance with a second coding method and by which second coding means, as a result of coding in accordance with said second coding method, at the most a given number M of coding signals representing a data block can be generated and supplied, the number M being smaller than the number N, and there have been provided selection means with the aid of which it is possible to select that the coding signals representing a data block and supplied by the first coding means or that the coding signals representing a data block and supplied by the second coding means can be applied to the amplitude modulation means. By means of the measures in accordance with the invention it is achieved in a very simple manner and with only minimal additional cost that in a write/read device in accordance with the invention it is possible to choose from two coding possibilities or coding methods, so that it is possible either to select a coding method in which high amplitudes can occur in the range of the sidebands but which has the advantage that it guarantees high transmission rates, i.e. a transmission which is as rapid as possible, or to select another coding method which only allows a lower transmission rate, i.e. a slower transmission, but which has the advantage that it guarantees particularly small amplitude values in the range of the sidebands, thereby ensuring that problems as regards statutory regulations relating to maximum permissible spurious emissions and the limitation of spurious emission are avoided.

In a write/read device in accordance with the invention the measures defined in Claim 3 have proved to be advantageous because it is thus the desired result is obtained with a minimal number of modulation steps in the modulated carrier signal per coded data block, which guarantees particularly small amplitude values in the range of the sidebands.

Various possibilities are available for the implementation of the selection means in a write/read device in accordance with the invention. However, it has proved to be particularly advantageous if the measures defined in Claim 4 are taken because this has appeared to be particularly favorable for implementation by means of a microcomputer.

The measures defined in Claims 5 and 6 have proved to be very advantageous because they guarantee that in a transponder which communicates with a write/read device in accordance with the invention the coding method selected for the data transmission in the

write/read device can be detected very simply and thus a correct decoding is guaranteed in the transponder.

The afore-mentioned as well as further aspects of the invention will become apparent from the example of an embodiment described hereinafter and will be elucidated with
5 reference to this example.

The invention will be described in more detail with reference to the drawings, which show two embodiments given by way of example, to which the invention is not limited.

10 Figure 1 is a block diagram of a relevant part of a write/read device in accordance with a first embodiment of the invention.

Figure 2A shows an example of a data block which occurs in the device of Figure 1.

15 Figures 2B to 2E show signals and signal waveforms which occur in the device of Figure 1 as a result of the data block shown in Figure 2A.

Figure 3 shows a write/read device in accordance with a second embodiment of the invention.

20 Figure 1 shows a write/read device 1, hereinafter briefly referred to as the device 1. The device 1 is designed for the contactless communication with a plurality of transponders, as is known since long.

The device 1 includes data supply means 2, which in the present case are formed by a memory. However, the data supply means 2 may alternatively be formed by other
25 means, for example by data generation means which generate and supply data in response to information applied to these means. The data supply means 2 are adapted to supply at least one data block DB. Such a data block DB can be formed by, for example, the data block E1 hex = 225 dec, as shown in Figure 2A. This data block can be represented in a binary manner by means of one byte if eight bits in total. The following description is based on this example.
30 However, it is to be noted that in the case that a data block corresponding to a decimal number having far more digits, this has the consequence that a binary representation of this block is possible only by means of a plurality of bytes having eight bits.

The device 1 includes a microcomputer 3 by means of which a multitude of means and functions are realized but in the present case only the relevant means will be described in more detail.

The first coding means 4 are implemented by means of the microcomputer 3.

5 The first coding means 4 make it possible to code a data block DB, which is supplied by the data supply means 2 and is applied to the first coding means 4 via a data input DI of the microcomputer 3, in accordance with a first coding method. The data input DI is shown as a serial input but it can also take the form of a parallel input. The first coding means 4 are adapted to carry out a bit-oriented coding method. In the present case the first coding means 4 are adapted to perform a coding method in accordance with a Return-To-Zero code. As a
10 result of the coding in accordance with this first coding method the first coding means 4 can generate and supply at the most a number N of coding signals representing a data block DB. In the present case the number N has the value $N = 8$ and the coding signals are formed by coding pulses KI, as can be seen in Figure 2B.

15 In the case that the first coding means 4 receive a data block DB corresponding to the decimal number "225" (225 dec) from the data supply means 2, the first coding means 4 supply a total of coding pulses KI, as is shown in Figure 2B, namely the coding pulses KI1, KI6, KI7 and KI8. In this respect it is to be noted that the coding pulse KI1 corresponds to the value 2^0 , a coding pulse KI2 to the value 2^1 , a coding pulse KI3 to the value 2^2 , a coding pulse
20 KI4 to the value 2^3 , a coding pulse KI5 to the value 2^4 , the coding pulse KI6 to the value 2^5 , the coding pulse KI7 to the value 2^6 , and the coding pulse KI8 to the value 2^7 . Each of these coding pulses KI has a duration of $9.44 \mu\text{s}$. The coding pulses KI are situated in a time frame comprising eight time frame portions, which each have a frame portion time T1 of $37.76 \mu\text{s}$. The coding pulses KI each time appear at the end of a frame time portion.

25 As regards the first coding means 4 it is to be noted that these means 4 are adapted to generate a first start signal SP1 which identifies the first coding method and which is supplied by the first coding means 4 before the coding signals KI which represent a data block, the number of coding signals being at the most equal to the given number $N = 8$. The first start signal SP1 has a duration of $10.88 \mu\text{s}$. This duration of $18.88 \mu\text{s}$ of the first start
30 signal SP1 is characteristic of the first coding method that can be carried out by the first coding means 4. Similarly to the coding pulses KI, the first start signal SP1 appears at the end of a time frame portion.

The device 1 further includes carrier signal generating means 5 for generating a carrier signal TS, which in the present case is a carrier signal having a frequency of 13.56 MHz.

5 The device 1 further includes modulation means, which in the present case are formed by amplitude modulation means 6. The amplitude modulation means 6 are arranged to receive the carrier signal TS and the coding signals, i.e. the coding pulses KI. With the aid of the amplitude modulation means 6 the carrier signal TS can be modulated in accordance with the coding pulses KI, so as to generate and supply an amplitude-modulated carrier signal TSM having a number of modulation steps MS equal to the number of coding pulses KI.

10 In the present case in accordance with Figures 2A and 2B a total of four modulation steps occur in the amplitude-modulated carrier signal TSM, which are referenced MS1, MS6, MS7 and MS8 in Figure 2C. Similarly to the coding pulses KI, the modulation steps MS are each time situated at the end of a frame time portion and advantageously occupy only half the duration of a frame time portion, which is favorable in view of minimal
15 amplitude values in the range of the sidebands of the amplitude-modulated carrier signal TSM. The modulation step in the amplitude-modulated carrier signal TSM which corresponds to the first start signal SP1 bears the reference MS0. The modulation depth is represented only diagrammatically in Figure 2C. In practice, it is advantageous to use a 10 % amplitude modulation (ASK 10 %). However, it is alternatively possible to use an ASK of 20 %, an ASK
20 of 30 % or an ASK of 50 %.

As is further apparent from Figure 2C, the amplitude-modulated carrier signal TSM corresponding to the data block DB = 225 dec requires a transmission time of 302.08 μ s. This means that the transmission of this amplitude-modulated carrier signal TSM and thus the transmission of the data word DW = 225 dec from the device 1 to a transponder which
25 communicates with the device 1 requires only a comparatively short length of time. However, owing to the occurrence of, in the present case, four modulation steps MS1, MS6, MS7 and MS8 within the transmission time interval of 302.08 μ s comparatively high amplitude values will occur in the range of the sidebands of the carrier signal TS. If all the eight modulation steps MS1 to MS8 occur the maximum amplitude values are reached in the range of the
30 sidebands of the carrier signal TS.

The device 1 finally comprises transmission means 7, which include a transmission coil 8. The transmission means 7 are arranged to receive the amplitude-modulated carrier signal TSM. The transmission means 7 transmit the amplitude-modulated

carrier signal TSM inductively to receiving means of a transponder which is in communication with the device 1.

The device 1 advantageously includes second coding means 9 with the aid of which a data block DB supplied by the data supply means 2 and applied to the second coding means 9 can be coded in accordance with a second coding method. The second coding means 9 are adapted to carry out a byte-oriented coding method. In the present case the second coding means 9 are adapted to carry out a coding method in accordance with a "1-out-of-K" code. Owing to the coding in accordance with this second coding method the second coding means 9 can generate and supply at the most a given number M of coding signals which represent a data block DB, the number M being smaller than the number N. In the present case this second coding method enables at the most the given number $M = 1$ of coding signals which represent a data block DB to be generated and supplied and the second coding means 9 supply coding signals in the form of coding pulses KI, as is apparent from Figure 2D.

As is further apparent from Figure 2D, the second coding means 9 in the present example, in which the data block DB = 225 dec shown in Figure 2A, supply a single coding pulse KI225. The coding pulse KI225 is situated in a time frame comprising 256 time frame portions, which each have a frame portion time T2 of 18.88 μ s. The coding pulse KI225 is situated in the 225th time frame portion, namely in such a way that it lies at the end of this time frame portion and continues till the end of this time frame portion. The coding pulse KI225 has a duration of 9.44 μ s, which corresponds to half the frame portion time T2 and which also applies to all the other possible coding pulses KI1 to KI256. The coding pulse KI225 which can be supplied by the second coding means 9 corresponds to one byte comprising eight (8) bits, namely the byte "10000111", corresponding to the coding pulses KI1, KI6, KI7 and KI8 which can be supplied by the first coding means 4.

As regards the second coding means 9 it is to be noted that the second coding means 9 are adapted to generate a second start signal SP2 which is characteristic of the second coding method, which start signal - as can be seen in Figure 2D - is supplied by the second coding means 9 before the coding signals which represent a data block, i.e. the coding pulse KI225, the number of coding signals being at the most equal to the given number $M = 1$.

With respect to the coding means 9 it is to be noted further that the second coding means 9 can be designed so as to guarantee that a given data block DB, preferably the data block that occurs most frequently and which for example corresponds to the decimal value zero, is coded in that for this data block DB no coding signal at all, i.e. no coding pulse KI, is generated and supplied, as a result of which no modulation step at all is generated for

this data block DB. This measure is advantageous in view of a reduction of the sideband level in conjunction with a so-called quasi-peak measurement.

The device 1 further includes selection means 10 which make it possible to select that either the coding signals KI representing a data block DB and supplied by the first
5 coding means 4 or the coding signals KI representing a data block DB and supplied by the second coding means 9 can be applied to the amplitude modulation means 6.

In the present case the selection means 10 include a control switch 11, which is controllable by hand but which also be controllable in another manner. The control switch 11 has one end connected to a potential, not indicated, and has its other end connected to an input
10 12 of the microcomputer 3. Arranged after the input 12 are control signal generating means 13, which are realized by means of the microcomputer 3 and which generate two different control signals SS1 and SS2 in dependence on the switching state of the control switch 11. When the control switch 11 is in its non-conductive switching state the control signal generating means 13 generate the first control signal SS1, while in the conductive switching state of the control
15 switch 11 said means generate the second control signal SS2.

The selection means 10 further include controllable switching means 14 arranged between, on the one hand, the first coding means 4 and the second coding means 9 and, on the other hand, an output 15 of the microcomputer 3, to which output the amplitude modulation means 6 are connected. This means that the switching means 14 are included, on
20 the one hand, the first coding means 4 and the second coding means 9 and, on the other hand, the amplitude modulation means 6.

When the control switch 11 is in its switching state shown in Figure 1 and, consequently, the control signal generating means 13 supply the first control information SS1 to the control input 16 of the switching means 14, this results in the switching means 14 being
25 in the switching state shown in Figure 1, in which state the second coding means 9 are connected to the amplitude modulation means 6.

When the second coding means 9 are connected to the amplitude modulation means 6 via the switching means 14 this results in the pulse train shown in Figure 2D being applied to the amplitude modulation means 6, as a result of which the amplitude-modulated
30 carrier signal TSM shown in Figure 2E is generated, in which only one modulation step, namely the modulation step referenced MS225, occurs after the modulation step MS0 initiated by the second start signal SP2.

As can be seen in Figure 2E, the transmission of the amplitude-modulated carrier signal TSM corresponding to the data block DB = 225 dec shown in Figure 2A requires

a total transmission time of 4.833 ms owing to the frame portion time T2 of 18.88 μ s. In comparison with the transmission time of 302.08 μ s in Figure 2 this is a substantially longer transmission time but in relation to the amplitude-modulated carrier signal TSM shown in Figure 2 it is to be noted that in the time interval of 4.833 ms only a single modulation step
5 occurs, namely the modulation step MS225, which has the advantageous result that the amplitude values in the range of the sidebands of the carrier signal TS are particularly small, so that no problems arise with statutory regulations relating to the effects of spurious emission and the limitation of spurious emission.

The device 1 described hereinbefore advantageously allows a choice between
10 two coding methods, so that at option either a coding method can be selected in which comparatively high amplitudes occur in the range of the sidebands of the carrier signal but which in an advantageous manner guarantees high transmission rates, i.e. a rapid transmission from the device to a transponder, or another coding method can be selected, which only permits a lower transmission rate, i.e. a slower transmission but which in an advantageous
15 manner guarantees particularly small amplitude values in the range of the sidebands of the carrier signal.

The device 1 shown in Figure 3 differs from the device 1 shown in Figure 1 in that it has selection means 10 by means of which it is possible to select whether the coding pulses KI supplied by the first coding means 4 or by the second coding means 9 are transferred
20 to the amplitude modulation means 6.

In the device 1 shown in Figure 3 the selection means 10 also include the first coding means 4 and the second coding means 9. In the present case, the first coding means 4 and the second coding means 9 each have a control input 17 and 18, respectively, which are arranged to receive the control signals SS1 and SS2 supplied by the control signal generating
25 means 13. Both coding means 4 and 9 are designed in such a manner that in the case that the first control signal SS1 is applied to the control inputs 17 and 18 of the two coding means 4 and 9 the first coding means 4 are set to an inactive state and the second coding means 9 are set to an active state, while in the case that the second control signal SS2 is applied to the control inputs 17 and 18 of the two coding means 4 and 9 the first coding means 4 are set to an
30 active state and the second coding means 9 are set to an inactive state. Thus, it is also achieved that when the control switch 11 is in its non-conductive state the second coding means 9 supply the coding pulses KI generated by them to the amplitude modulation means 6 and when the control switch 11 is in its conductive state the first coding means 4 supply the coding pulses KI generated by them to the amplitude modulation means 6.

With regard to the two devices 1 described hereinbefore it is to be noted that in the case that for the transmission of data supplied by the data supply means 2 not a single data block is used -as described hereinbefore for the sake of simplicity - but that a data block sequence comprising a plurality of data blocks is required for this, which sequence for example consists of n data blocks, the relevant coding means 4 or 9 only generate a start signal SP1 or SP2 before the first data block of each of such data block sequences.

The invention is not limited to the devices in accordance with the two embodiments described hereinbefore by way of example. When this is appropriate the second coding means may also be adapted to carry out a coding method in accordance with a "2-out-of-K" code or a "4-out-of-K" code. Moreover, when the first coding means are active a comparatively low amplitude of the carrier signal may be selected, in which case only a comparatively small transmission range can be obtained but it is also achieved that low amplitudes can be obtained in the range of the sidebands of the carrier signal. Furthermore, it is to be noted that, if desired, a device in accordance with the invention may also include third coding means with the aid of which a third coding method can be carried out in order to apply coding signals coded in accordance with a third coding method to the amplitude modulation means for the purpose of amplitude modulation of the carrier signal. It is to be noted that instead of amplitude modulation means other modulation means may be used, for example frequency modulation means or phase modulation means, enabling for example frequency shift keying or phase shift keying, for example by 180° , to be carried out.

CLAIMS:

1. A write/read device (1)
designed for the contactless communication with at least one transponder and
comprising data supply means (2) for supplying at least one data block (DB) and
including first coding means (4), by which first coding means (4) a data block (DB) supplied
5 by the data supply means (2) and applied to said first coding means (4) can be coded in
accordance with a first coding method and by which, as a result of the coding in accordance
with this first coding method, at the most a given number N of coding signals (KI)
representing a data block (DB) can be generated and supplied, and
including carrier signal generating means (5) for generating a carrier signal (TS) and
10 including modulation means (6), to which modulation means (6) the carrier signal (TS) and the
coding signals (KI) can be applied and by which modulation means (6) the carrier signal (TS)
can be modulated in accordance with the coding signals (KI) so as to generate and supply a
modulated carrier signal (TSM) corresponding to the number of coding signals (KI) and
having the same number of modulation steps, and
15 including transmission means (7), to which transmission means (7) the modulated carrier
signal (TSM) can be applied in order to be transmitted to at least one transponder,
characterized in that
there have been provided second coding means (9), by which second coding means (9) a data
block (DB) supplied by the data supply means (2) and applied to said second coding means (9)
20 can be coded in accordance with a second coding method and by which second coding means
(9), as a result of coding in accordance with said second coding method, at the most a given
number M of coding signals representing a data block (DB) can be generated and supplied,
the number M being smaller than the number N, and
there have been provided selection means (10), with the aid of which selection means (10) it is
25 possible to select that the coding signals (KI) representing a data block (DB) and supplied by
the first coding means (4) or that the coding signals (KI) representing a data block (DB) and
supplied by the second coding means (9) can be applied to the amplitude modulation means
(6).

2. A device (1) as claimed in Claim 1, characterized in that the second coding means (9) are adapted to carry out a byte-oriented coding method.

3. A device (1) as claimed in Claim 2, characterized in that
5 the second coding means (9) are adapted to carry out a coding method in accordance with a "1-out-of-K" code.

4. A device (1) as claimed in Claim 1, characterized in that the selection means (10) include switching means (14) arranged between, on the one hand, the
10 first coding means (4) and the second coding means (9) and, on the other hand, the modulation means (6).

5. A device (1) as claimed in Claim 1, characterized in that the first coding means (4) are adapted to generate a first start signal (SP1) characteristic of the
15 first coding method, which start signal can be supplied by the first coding means (4) before the coding signals (KI) representing a data block (DB), the number of these coding signals being at the most equal to the given number N.

6. A device (1) as claimed in Claim 1, characterized in that
20 the second coding means (9) are adapted to generate a second start signal (SP2) characteristic of the second coding method, which start signal can be supplied by the second coding means (9) before the coding signals (KI) representing a data block (DB), the number of these coding signals being at the most equal to the given number M.

1/2







FIG.1

DB=E1 hex=225 dec

FIG.2A



212





INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

<p>(51) International Patent Classification ⁷ : H03M 13/35, H04B 1/59</p>	<p>A3</p>	<p>(11) International Publication Number: WO 99/62196</p> <p>(43) International Publication Date: 2 December 1999 (02.12.99)</p>
<p>(21) International Application Number: PCT/IB99/00880</p> <p>(22) International Filing Date: 14 May 1999 (14.05.99)</p> <p>(30) Priority Data: 98890149.2 22 May 1998 (22.05.98) EP</p> <p>(71) Applicant: KONINKLIJKE PHILIPS ELECTRONICS N.V. [NL/NL]; Groenewoudseweg 1, NL-5621 BA Eindhoven (NL).</p> <p>(71) Applicant (for SE only): PHILIPS AB [SE/SE]; Kottbygatan 7, Kista, S-164 85 Stockholm (SE).</p> <p>(72) Inventor: AMTMANN, Franz; Prof. Holstlaan 6, NL-5656 AA Eindhoven (NL).</p> <p>(74) Agent: WEBER, Helmut; Prof. Holstlaan 6, NL-5656 AA Eindhoven (NL).</p>		<p>(81) Designated States: JP, European patent (AT, BE, CH, CY, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE).</p> <p>Published <i>With international search report.</i> <i>Before the expiration of the time limit for amending the claims and to be republished in the event of the receipt of amendments.</i></p> <p>(88) Date of publication of the international search report: 3 February 2000 (03.02.00)</p>
<p>(54) Title: WRITE/READ DEVICE FOR COMMUNICATION WITH TRANSPONDERS, HAVING FIRST CODING MEANS AND SECOND CODING MEANS</p> <div data-bbox="305 1171 1271 1696"> </div> <p>(57) Abstract</p> <p>A write/read device (1) for the contactless communication with at least one transponder has first coding means (4) for coding a data block (DB) in accordance with a first coding method, which first coding means (4) can generate at the most a given number of N coding signals (KI) per data block (DB) in accordance with this first coding method, and has second coding means (9) for coding a data block (DB) in accordance with a second coding method, which second coding means (9) can generate at the most a given number of M coding signals (KI) per data block (DB) in accordance with this second coding method, and has selection means (10) for the selection between the coding signals (KI) supplied by the first coding means (4) and the coding signals (KI) supplied by the second coding means (9).</p>		

FOR THE PURPOSES OF INFORMATION ONLY

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AL	Albania	ES	Spain	LS	Lesotho	SI	Slovenia
AM	Armenia	FI	Finland	LT	Lithuania	SK	Slovakia
AT	Austria	FR	France	LU	Luxembourg	SN	Senegal
AU	Australia	GA	Gabon	LV	Latvia	SZ	Swaziland
AZ	Azerbaijan	GB	United Kingdom	MC	Monaco	TD	Chad
BA	Bosnia and Herzegovina	GE	Georgia	MD	Republic of Moldova	TG	Togo
BB	Barbados	GH	Ghana	MG	Madagascar	TJ	Tajikistan
BE	Belgium	GN	Guinea	MK	The former Yugoslav Republic of Macedonia	TM	Turkmenistan
BF	Burkina Faso	GR	Greece	ML	Mali	TR	Turkey
BG	Bulgaria	HU	Hungary	MN	Mongolia	TT	Trinidad and Tobago
BJ	Benin	IE	Ireland	MR	Mauritania	UA	Ukraine
BR	Brazil	IL	Israel	MW	Malawi	UG	Uganda
BY	Belarus	IS	Iceland	MX	Mexico	US	United States of America
CA	Canada	IT	Italy	NE	Niger	UZ	Uzbekistan
CF	Central African Republic	JP	Japan	NL	Netherlands	VN	Viet Nam
CG	Congo	KE	Kenya	NO	Norway	YU	Yugoslavia
CH	Switzerland	KG	Kyrgyzstan	NZ	New Zealand	ZW	Zimbabwe
CI	Côte d'Ivoire	KP	Democratic People's Republic of Korea	PL	Poland		
CM	Cameroon	KR	Republic of Korea	PT	Portugal		
CN	China	KZ	Kazakhstan	RO	Romania		
CU	Cuba	LC	Saint Lucia	RU	Russian Federation		
CZ	Czech Republic	LI	Liechtenstein	SD	Sudan		
DE	Germany	LK	Sri Lanka	SE	Sweden		
DK	Denmark	LR	Liberia	SG	Singapore		
EE	Estonia						

INTERNATIONAL SEARCH REPORT

International application No.

PCT/IB 99/00880

A. CLASSIFICATION OF SUBJECT MATTER		
IPC7: H03M 13/35, H04B 1/59 According to International Patent Classification (IPC) or to both national classification and IPC		
B. FIELDS SEARCHED		
Minimum documentation searched (classification system followed by classification symbols)		
IPC7: H03M, H04B, H04L		
Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched		
SE,DK,FI,NO classes as above		
Electronic data base consulted during the international search (name of data base and, where practicable, search terms used)		
C. DOCUMENTS CONSIDERED TO BE RELEVANT		
Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	EP 0680158 A1 (AT&T CORP.), 2 November 1995 (02.11.95), column 6, line 46 - column 7, line 12, figure 3 --	1-6
A	US 4047151 A (NILS R.C. RYDBECK ET AL), 6 Sept 1977 (06.09.77), column 4, line 5 - line 61 --	1-6
A	US 5214656 A (HONG Y. CHUNG ET AL), 25 May 1993 (25.05.93), column 3, line 56 - column 5, line 26, figure 1 --	1-6
<input checked="" type="checkbox"/> Further documents are listed in the continuation of Box C. <input checked="" type="checkbox"/> See patent family annex.		
* Special categories of cited documents "A" document defining the general state of the art which is not considered to be of particular relevance "E" earlier document but published on or after the international filing date "I" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified) "O" document referring to an oral disclosure, use, exhibition or other means "P" document published prior to the international filing date but later than the priority date claimed "I" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention "X" document of particular relevance: the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone "Y" document of particular relevance: the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art "&" document member of the same patent family		
Date of the actual completion of the international search		Date of mailing of the international search report
9 December 1999		11 -12- 1999
Name and mailing address of the ISA Swedish Patent Office Box 5055, S-102 42 STOCKHOLM Facsimile No. +46 8 666 02 86		Authorized officer Christian Rasch/mj Telephone No. +46 8 782 25 00

INTERNATIONAL SEARCH REPORT

International application No.

PCT/IB 99/00880

C (Continuation). DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	US 5377194 A (ARTHUR R. CALDERBANK), 27 December 1994 (27.12.94), column 3, line 27 - column 4, line 9, figure 1 -- -----	1-6

INTERNATIONAL SEARCH REPORT

02/11/99

International application No.

PCT/IB 99/00880

Patent document cited in search report			Publication date	Patent family member(s)		Publication date
EP	0680158	A1	02/11/95	CA	2145568 A	30/10/95
				JP	8167866 A	25/06/96
				US	5546420 A	13/08/96

US	4047151	A	06/09/77	NONE		

US	5214656	A	25/05/93	DE	69125115 D,T	19/06/97
				EP	0490552 A,B	17/06/92
				HK	118797 A	05/09/97
				JP	4302550 A	26/10/92

US	5377194	A	27/12/94	CA	2083725 A	17/06/93
